



NAPCO[®]

333 Bayview Avenue
Amityville, New York 11701
For Sales and Repairs, (800) 645-9445
For Technical Service, (800) 645-9440
Publicly traded on NASDAQ Symbol: NSSC

© NAPCO 2005

Quick-Modem

INSTALLATION INSTRUCTIONS

WI1066C 5/05

GENERAL DESCRIPTION

The NAPCO Quick-Modem is a modem which is fully compatible with the NAPCO Quickloader PCD3000, PCD2000 and PCD-Windows Quickloader V4.54 (or higher) downloader programs.

SPECIFICATIONS

Input Power: 9 VAC, 750-1000mA, 9.8 W (from supplied AC adapter).

CONNECTION

Connect the Quick-Modem to the J2 connector of the PCI2000 Interface module using a standard modem cable (not supplied).

CONFIGURATION

PCD3000, PCD2000 and PCD-Windows Quickloader software must be configured as follows for use with the Quick-Modem:

PCD3000

From the PCD main screen (*teal screen with the large NAPCO logo*):

Press **S** for **Setup**

Press **M** for **Modem Setup**

Select the **StarComm 2400 Data (model 2400E-030)** modem

Modem type **(Select StarComm 2400 Data (model 2400E-030))**

port none COM1 COM2 COM3 COM4

(*select the Comm port for Quick-Modem*)

physical type	external	internal	
carrier detect	slow	fast	
call monitor	none	connect	always
		(<i>select preference</i>)	
speaker volume	1 2 3 4		
	(<i>select preference</i>)		

Telephone line:

dialing mode	rotary	TouchTone
dialtone type	nonstandard	standard
telephone number		
dial-out prefix		

- Press [ESC]
- Press **X** for **EXit**

The settings will be checked for errors. If none are found, a message will display:

[Local Configuration values changed]
Save changes?

- Press [Y] to accept the changes and exit Setup.

PCD2000

Go to the DOS directory in which PCD2000 is installed cd\PCD2000 (*or the directory name in which PCD2000 is installed*).

- Type **SETUP**
- Select option **A** Basic Setup

PCI Module installed? **Yes** No

NAPCO Security Systems, Inc.
333 Bayview Avenue • Amityville, New York 11701
For Sales and Repairs, call Toll Free: (800) 645-9445

For Technical Assistance, Contact the NAPCO
Toll Free Helpline ☎ (800) 645-9440

PCI Module serial port? COM1 COM2 COM3 COM4
(select the Comm port for PCI2000 Interface module)

Modem installed? **Yes** No

Modem type? Internal **External**

Modem serial port? COM1 COM2 COM3 COM4
(select the Comm port for Quick-Modem)

Modem dialing mode? **TouchTone** Rotary

Monitor call through speaker? Always Connect No
(select preference)

Speaker volume? 1 2 3 4
(select preference)

Modem Model? **StarComm 2400 Data (model 2400E-030)**

Dialing Prefix

Display type? RGB/Monochrome LCD/Composite
(select preference)

Time Zone offset (hours) 08
(set time zone - press [F2] for list of settings)

Daylight savings observed Yes No

- Press [ESC]

A dialog box will now pop up with the question: "Is PCI2000 clicking" and you should hear a clicking sound coming from the PCI2000.

If you hear the PCI clicking, press [Y]. If not press [N], and you will see a list of possible causes.

PCD-Windows Quickloader

PCD-Windows Quickloader download software must be configured as follows for use with the Quick-Modem:

Click **File, Modem Settings** to open the **Serial Communication Setup** dialog (see image below).

NOTE: Although image below displays "Com 1" in the Port fields, the Port number may be different in your system.

Select a *Port* to be used with the Quick-Modem. Enter a *Dial-out Prefix* (if required) and the *Telephone Number*. Select a *PCI Port* from the drop-down menu.

For *Modem Type*, select "**Napco Quick-modem - StarComm 2400 Data (Model 2400E-030)**".

