

T1656

Open Frame Transformer

Description

Altronix T1656 open frame transformer provides power for electronic power supplies and equipment including security, access control, and surveillance devices.



| Input | | Physical and Environmental | |
|---------|------------------------|--|--------------------------------|
| Voltage | 115VAC, 50/60Hz, 0.5A. | Please see the drawing below for dimensions. | |
| | | Product Weight | 1.8 lbs. (0.82 kg). |
| Outputs | | Shipping Weight | 2.5 lbs. (1.14 kg). |
| Voltage | 16VAC (56VA). | Temperature | |
| Current | 3.5A. | Operating | 0°C to 49°C (32°F to 120°F). |
| | | Storage | -20°C to 70°C (-4°F to 158°F). |
| | | Relative Humidity | 85% +/-5%. |
| | | BTU/Hr. (approx.: | 29 BTU/Hr. |

Transformer Drawing and Dimensions

